



# ISOTOP® Boost chopper Super Junction MOSFET Power Module





#### **Application**

- AC and DC motor control
- Switched Mode Power Supplies
- Power Factor Correction
- Brake switch

#### **Features**



- Ultra low R<sub>DSon</sub>
- Low Miller capacitance
- Ultra low gate charge
- Avalanche energy rated

#### • SiC Schottky Diode

- Zero reverse recovery
- Zero forward recovery
- Temperature Independent switching behavior
- Positive temperature coefficient on VF
- ISOTOP® Package (SOT-227)
- Very low stray inductance
- High level of integration

#### Benefits

- Outstanding performance at high frequency operation
- Stable temperature behavior
- Very rugged
- Direct mounting to heatsink (isolated package)
- Low junction to case thermal resistance
- Easy paralleling due to positive TC of VCEsat
- RoHS Compliant

## Absolute maximum ratings

Symbol	Parameter		Max ratings	Unit
$V_{ m DSS}$	Drain - Source Breakdown Voltage		600	V
Ţ	Continuous Drain Current $T_c = 25$		50	
$I_D$	Continuous Drain Current	$T_c = 80$ °C	38	Α
$I_{DM}$	Pulsed Drain current		130	
$V_{GS}$	Gate - Source Voltage		±20	V
$R_{DSon}$	Drain - Source ON Resistance		45	mΩ
$P_{D}$	Maximum Power Dissipation	$T_c = 25^{\circ}C$	290	W
$I_{AR}$	Avalanche current (repetitive and non repetitive)		15	A
$E_{AR}$	Repetitive Avalanche Energy		3	m I
$E_{AS}$	Single Pulse Avalanche Energy		1900	mJ

CAUTION: These Devices are sensitive to Electrostatic Discharge. Proper Handing Procedures Should Be Followed.

1 - 4



## All ratings @ $T_j = 25$ °C unless otherwise specified

## **Electrical Characteristics**

Symbol	Characteristic	Test Conditions		Min	Тур	Max	Unit
T	Zero Gate Voltage Drain Current	$V_{GS} = 0V, V_{DS} = 600V$	$T_j = 25^{\circ}C$			250	4
$I_{ m DSS}$		$V_{GS} = 0V, V_{DS} = 600V$	$T_j = 125$ °C			500	μΑ
R <sub>DS(on)</sub>	Drain – Source on Resistance	$V_{GS} = 10V, I_D = 22.5A$			40	45	mΩ
$V_{GS(th)}$	Gate Threshold Voltage	$V_{GS} = V_{DS}$ , $I_D = 3mA$		2.1	3	3.9	V
$I_{GSS}$	Gate – Source Leakage Current	$V_{GS} = \pm 20 \text{ V}, V_{DS} = 0 \text{ V}$				100	nA

**Dynamic Characteristics** 

Symbol	Characteristic	Test Conditions		Min	Тур	Max	Unit
$C_{iss}$	Input Capacitance	$V_{GS} = 0V ; V_{DS} = 25$	V		6.8		nF
$C_{oss}$	Output Capacitance	f = 1MHz			0.32		111
$Q_{g}$	Total gate Charge	$V_{GS} = 10V$			150		
$Q_{gs}$	Gate – Source Charge	$V_{\text{Bus}} = 300\text{V}$			34		nC
$Q_{gd} \\$	Gate – Drain Charge	$I_D = 44A$			51		
$T_{d(on)}$	Turn-on Delay Time	Tj=25°C			30		
$T_{\rm r}$	Rise Time	$V_{GS} = 10V$			20		
$T_{d(off)}$	Turn-off Delay Time	$V_{\text{Bus}} = 400V$ $I_{\text{D}} = 44A$			100		ns
$T_{\mathrm{f}}$	Fall Time	$R_G = 3.3\Omega$			20		
Eon	Turn-on Switching Energy	$\begin{aligned} &\textbf{Tj=25^{\circ}C} \\ &\textbf{V}_{GS} = 10 \textbf{V} \; ; \textbf{V}_{Bus} = 400 \textbf{V} \\ &\textbf{I}_{D} = 44 \textbf{A} \; ; \textbf{R}_{G} = 3.3 \Omega \\ &\textbf{Tj=125^{\circ}C} \\ &\textbf{V}_{GS} = 10 \textbf{V} \; ; \textbf{V}_{Bus} = 400 \textbf{V} \\ &\textbf{I}_{D} = 44 \textbf{A} \; ; \textbf{R}_{G} = 3.3 \Omega \end{aligned}$			405		т
E <sub>off</sub>	Turn-off Switching Energy				520		μJ
$E_{on}$	Turn-on Switching Energy				660		., Т
$E_{\text{off}}$	Turn-off Switching Energy				635		μJ
$V_{\mathrm{SD}}$	Diode Forward Voltage	$V_{GS} = 0V, I_S = -44A$			0.9	1.2	V
$t_{rr}$	Reverse Recovery Time	$I_S = -44A$ $V_R = 400V$	$T_j = 25$ °C		600		ns
$Q_{rr}$	Reverse Recovery Charge	$di_{S}/dt = 100A/\mu s$	$T_j = 25$ °C		17		μC

SiC chopper diode ratings and characteristics


Symbol	Characteristic	Test Conditions		Min	Typ	Max	Unit
$V_{RRM}$	Maximum Peak Repetitive Reverse Voltage			600			V
$I_{RM}$	Maximum Reverse Leakage Current	V <sub>R</sub> =600V	$T_{j} = 25^{\circ}C$ $T_{j} = 175^{\circ}C$		100 200	400 2000	μА
I <sub>F(AV)</sub>	Maximum Average Forward Current	50% duty cycle	Tc = 125°C		20		A
$V_{\mathrm{F}}$	Diode Forward Voltage	$I_F = 20A$	$T_{j} = 25^{\circ}C$ $T_{j} = 175^{\circ}C$		1.6	1.8	V
Qc	Total Capacitive Charge	$I_F = 20A, V_R = 300V$ di/dt = $800A/\mu s$			28		nC
Q	Tetal Conseitence	$f = 1 MHz, V_R = 200 V$			130		ъE
	Total Capacitance	$f = 1MHz, V_R =$	= 400V	·	100		pF



## Thermal and package characteristics

Symbol	Characteristic		Min	Тур	Max	Unit
$R_{thJC}$	Junction to Case Thermal Resistance	CoolMos			0.43	
		SiC Diode			1.4	°C/W
$R_{thJA}$	Junction to Ambient (IGBT & Diode)				20	
$V_{ISOL}$	RMS Isolation Voltage, any terminal to case t = 1 min, I isol<1mA, 50/60Hz		2500			V
$T_{J}, T_{STG}$	Storage Temperature Range		-40		150	°C
$T_{ m L}$	Max Lead Temp for Soldering:0.063" from case for 10 sec				300	C
Torque	Mounting torque (Mounting = 8-32 or 4mm Machine and terminals = 4mm Machine)				1.5	N.m
Wt	Package Weight			29.2		g

## **SOT-227 (ISOTOP®) Package Outline**



"COOLMOSTM comprise a new family of transistors developed by Infineon Technologies AG. "COOLMOS" is a trademark of Infineon Technologies AG".

ISOTOP® is a registered trademark of ST Microelectronics NV



#### **DISCLAIMER**

The information contained in the document (unless it is publicly available on the Web without access restrictions) is PROPRIETARY AND CONFIDENTIAL information of Microsemi and cannot be copied, published, uploaded, posted, transmitted, distributed or disclosed or used without the express duly signed written consent of Microsemi. If the recipient of this document has entered into a disclosure agreement with Microsemi, then the terms of such Agreement will also apply. This document and the information contained herein may not be modified, by any person other than authorized personnel of Microsemi. No license under any patent, copyright, trade secret or other intellectual property right is granted to or conferred upon you by disclosure or delivery of the information, either expressly, by implication, inducement, estoppels or otherwise. Any license under such intellectual property rights must be approved by Microsemi in writing signed by an officer of Microsemi.

Microsemi reserves the right to change the configuration, functionality and performance of its products at anytime without any notice. This product has been subject to limited testing and should not be used in conjunction with life-support or other mission-critical equipment or applications. Microsemi assumes no liability whatsoever, and Microsemi disclaims any express or implied warranty, relating to sale and/or use of Microsemi products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. Any performance specifications believed to be reliable but are not verified and customer or user must conduct and complete all performance and other testing of this product as well as any user or customers final application. User or customer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the customer's and user's responsibility to independently determine suitability of any Microsemi product and to test and verify the same. The information contained herein is provided "AS IS, WHERE IS" and with all faults, and the entire risk associated with such information is entirely with the User. Microsemi specifically disclaims any liability of any kind including for consequential, incidental and punitive damages as well as lost profit. The product is subject to other terms and conditions which can be located on the web at http://www.microsemi.com/legal/tnc.asp

#### Life Support Application

Seller's Products are not designed, intended, or authorized for use as components in systems intended for space, aviation, surgical implant into the body, in other applications intended to support or sustain life, or for any other application in which the failure of the Seller's Product could create a situation where personal injury, death or property damage or loss may occur (collectively "Life Support Applications").

Buyer agrees not to use Products in any Life Support Applications and to the extent it does it shall conduct extensive testing of the Product in such applications and further agrees to indemnify and hold Seller, and its officers, employees, subsidiaries, affiliates, agents, sales representatives and distributors harmless against all claims, costs, damages and expenses, and attorneys' fees and costs arising, directly or directly, out of any claims of personal injury, death, damage or otherwise associated with the use of the goods in Life Support Applications, even if such claim includes allegations that Seller was negligent regarding the design or manufacture of the goods.

Buyer must notify Seller in writing before using Seller's Products in Life Support Applications. Seller will study with Buyer alternative solutions to meet Buyer application specification based on Sellers sales conditions applicable for the new proposed specific part.

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Microchip:

APT50N60JCCU2